



Bridge with AP mode

Connect via cable to the DAP-1360. Change the computers address to 192.168.0.55, then go to your web browser and type in 192.168.0.50 or dlinkap.

Username: admin password is blank

Login to the DAP-1360



LOGIN
Login in the Access Point

User Name :
Password :

WIRELESS

Once you are logged in click on Wireless Setup and then change the Wireless Mode to Bridge with AP (WDS with AP).

DAP-1360 //	SETUP	ADVANCED	MAINTENANCE	STATUS
WIZARD	WIRELESS NETWORK			
WIRELESS SETUP	Use this section to configure the wireless settings for your D-Link Access Point. Please note that changes made on this section may also need to be duplicated on your wireless client.			
LAN SETUP	To protect your privacy you can configure wireless security features. This device supports three wireless security modes including: WEP or WPA and WPA2.			
LOGOUT	<input type="button" value="Save Settings"/> <input type="button" value="Don't Save Settings"/>			
<input type="button" value="Reboot"/>	WIRELESS NETWORK SETTINGS :			
	Enable Wireless : <input checked="" type="checkbox"/> Always <input type="button" value="Add New"/>			
	Wireless Mode : <input type="text" value="Bridge with AP"/> <input type="button" value="Site Survey"/>			

Set the Wireless Network Name, change the Wireless Channel to 1, 6 or 11. In Bridge with AP mode all DAP-1360's need to be on the same channel.

Your Wireless Network Name (SSID), Password and security settings must be the same on all the devices.

The 802.11 Mode should be on Mixed 802.11n, 802.11g and 802.11b. Security Mode can be on Enable WPA2.

Cipher Type you can change to Auto. PSK/EAP you can set to Personal. The Passphrase you can set to anything you want, no special characters and minimum of 8 characters.

WIRELESS NETWORK SETTINGS :

Enable Wireless : Always

Wireless Mode :

Wireless Network Name : (Also called the SSID)

Enable Auto Channel Scan :

Wireless Channel :

802.11 Mode :

Channel Width :

Transmission Rate :

Enable Hidden Wireless : (Also called Disable SSID Broadcast)

WIRELESS SECURITY MODE :

Security Mode :

WPA2 :

WPA2 requires stations to use high grade encryption and authentication.

Cipher Type :

PSK / EAP :

Passphrase :

Confirmed Passphrase :

The **first** DAP-1360 will need to be connected via cable to the router after being setup and the rest will be connected via wireless. Disable the wireless on the router.

Bridge with AP mode works with up to 8 DAP-1360's connected to each other.

NOTE: Don't enter the MAC address of the first DAP-1360 into the "Remote AP MAC" of the last DAP-1360, it will create a loop.

Please see examples below.

Example of what the topology will look like.



In Bridge Settings at Remote AP MAC you will enter:

1. On the first DAP-1360 the MAC address of the second DAP-1360. Please see below picture.

WIRELESS NETWORK

Use this section to configure the wireless settings for your D-Link Access Point. Please note that changes made on this section may also need to be duplicated on your wireless client.

To protect your privacy you can configure wireless security features. This device supports three wireless security modes including: WEP or WPA and WPA2.

WIRELESS NETWORK SETTINGS :

Enable Wireless : Always

Wireless Mode : Bridge with AP

Wireless Network Name : dlink (Also called the SSID)

Enable Auto Channel Scan :

Wireless Channel : 6

802.11 Mode : Mixed 802.11n, 802.11g and 802.11b

Channel Width : Auto 20/40MHz

Transmission Rate : Auto

Enable Hidden Wireless : (Also called Disable SSID Broadcast)

WIRELESS SECURITY MODE :

Security Mode : Enable WPA2-Auto Wireless Security (enhanced)

WPA2-AUTO :

WPA2-Auto requires stations to use high grade encryption and authentication.

Cipher Type : AUTO

PSK / EAP : Personal

Passphrase :

Confirmed Passphrase :

BRIDGE SETTING :

Remote AP Mac: 1. 2.

3. 4.

5. 6.

7. 8.

Bridge Security: none

WEP Key: ASCII

Passphrase:

(8~63 char.)

2. On the second DAP-1360 the MAC address of the first and third DAP-1360. Please see below picture.

WIRELESS NETWORK

Use this section to configure the wireless settings for your D-Link Access Point. Please note that changes made on this section may also need to be duplicated on your wireless client.

To protect your privacy you can configure wireless security features. This device supports three wireless security modes including: WEP or WPA and WPA2.

WIRELESS NETWORK SETTINGS :

Enable Wireless : Always

Wireless Mode : Bridge with AP (Also called the SSID)

Wireless Network Name : dlink

Enable Auto Channel Scan :

Wireless Channel : 6

802.11 Mode : Mixed 802.11n, 802.11g and 802.11b

Channel Width : Auto 20/40MHz

Transmission Rate : Auto

Enable Hidden Wireless : (Also called Disable SSID Broadcast)

WIRELESS SECURITY MODE :

Security Mode : Enable WPA2-Auto Wireless Security (enhanced)

WPA2-AUTO :

WPA2-Auto requires stations to use high grade encryption and authentication.

Cipher Type : AUTO

PSK / EAP : Personal

Passphrase :

Confirmed Passphrase :

BRIDGE SETTING :

Remote AP Mac: 1. 2.

3. 4.

5. 6.

7. 8.

Bridge Security: none

WEP Key: ASCII

Passphrase: (8~63 char.)

3. On the third DAP-1360 the MAC address of the second and fourth DAP-1360. Please see below picture.

WIRELESS NETWORK

Use this section to configure the wireless settings for your D-Link Access Point. Please note that changes made on this section may also need to be duplicated on your wireless client.

To protect your privacy you can configure wireless security features. This device supports three wireless security modes including: WEP or WPA and WPA2.

WIRELESS NETWORK SETTINGS :

Enable Wireless : Always

Wireless Mode : Bridge with AP

Wireless Network Name : dlink (Also called the SSID)

Enable Auto Channel Scan :

Wireless Channel : 6

802.11 Mode : Mixed 802.11n, 802.11g and 802.11b

Channel Width : Auto 20/40MHz

Transmission Rate : Auto

Enable Hidden Wireless : (Also called Disable SSID Broadcast)

WIRELESS SECURITY MODE :

Security Mode : Enable WPA2-Auto Wireless Security (enhanced)

WPA2-AUTO :

WPA2-Auto requires stations to use high grade encryption and authentication.

Cipher Type : AUTO

PSK / EAP : Personal

Passphrase :

Confirmed Passphrase :

BRIDGE SETTING :

Remote AP Mac:	1. <input type="text"/>	2. <input type="text"/>
	3. <input type="text"/>	4. <input type="text"/>
	5. <input type="text"/>	6. <input type="text"/>
	7. <input type="text"/>	8. <input type="text"/>

Bridge Security: none

WEP Key: ASCII

Passphrase:

(8~63 char.)

NOTE: Don't enter the MAC address of the first DAP-1360 into the "Remote AP MAC" of the last DAP-1360, it will create a loop.

Bridge with AP mode works with up to 8 DAP-1360's connected to each other.