



DSL-2750U 3G Internet Setup Guide.

You can download the latest 3G compatibility list for the above mentioned router from the link below:

[ftp://ftp.d-link.co.za/DSL/DSL-2750u%20\(Retail\)/Compatibility%20Lists%203G/DSL-2750U%20Hardware%20Ver%20T3/](ftp://ftp.d-link.co.za/DSL/DSL-2750u%20(Retail)/Compatibility%20Lists%203G/DSL-2750U%20Hardware%20Ver%20T3/)

Connect with cable to the DSL-2750U.

Once you are connected open your web browser (Internet Explorer, Google Chrome and Firefox).

Type 10.0.0.2 and press Enter.



Username: admin

Password: admin

After entering the username and password click "Login".

You will be directed to the main menu. See below screenshot.

The screenshot shows the D-Link DSL2750U web interface. At the top, it displays 'Product Page: DSL2750U' and 'Firmware Version: AF_2.00_R03'. The main header features the D-Link logo. Below this is a navigation menu with tabs for 'SETUP', 'ADVANCED', 'MAINTENANCE', 'STATUS', and 'HELP'. The left sidebar contains a list of menu items: Wizard, ADSL Interface, Layer2 Interface, WAN Internet Setup, 3G Internet Setup, Wireless Connection, Local Network, IPv6 Local Network, Time and Date, Print Server, and Logout. The main content area is titled 'SETTING UP YOUR INTERNET' and contains the following text: 'There are two ways to set up your Internet connection. You can use the Web-based Internet Connection Setup Wizard or you can manually configure the connection. Please make sure you have your ISP's connection settings first if you choose manual setup.' Below this is the 'INTERNET CONNECTION WIZARD' section, which states: 'You can use this wizard for assistance and quick connection of your new D-Link Router to the Internet. You will be presented with step-by-step instructions in order to get your Internet connection up and running. Click the button below to begin.' A 'Setup Wizard' button is visible. A note at the bottom of the wizard section reads: 'Note: Before launching the wizard, please ensure you have correctly followed the steps outlined in the Quick Installation Guide included with the router.' On the right side, there is a 'Helpful Hints...' section with instructions for first-time users and advanced users.

On the left side you will see 3G Internet Setup.

The screenshot shows the D-Link DSL2750U web interface with the '3G MOBILE SETUP' page selected. The navigation menu and sidebar are the same as in the previous screenshot. The main content area is titled '3G MOBILE SETUP' and contains the following text: 'Choose Add, Remove or Edit to configure a WAN service For 3G Mobile interface. Note: If user manually connect up the 3G connection by clicking the 'Manual Dial' button, it will always stay connected, even when DSL connection is back alive.' Below this is the 'WIDE AREA NETWORK (WAN) SERVICE FOR 3G MOBILE SETUP' section, which displays 'modem status: NO USB CARD'. A table with the following columns is shown: Interface, Description, Type, Edit, and Action. At the bottom of the page, there are five buttons: 'Add', 'Remove', 'Information', 'Pin Manage', and 'Upload Driver'.

By default there isn't any entries made for 3G internet.

Click "Add".

Below screenshot shows what the 3G settings should look like on the router.

3G USB MOBILE MODEM SETUP

This screen allows you to configure a 3G wan interface.

WIDE AREA NETWORK (WAN) SERVICE FOR 3G MOBILE SETUP

Support NDIS

User Name:

Password:

Authentication Method:

APN:

Dial Number:

Dial on demand

Default WAN Connection Select:

WAN backup mechanism: DSL IP connectivity

Once you have all the correct settings, click “Apply/Save”. When the settings are saved you will be redirected back to the main screen, as seen below.

Please take note of the below modem statuses and their meanings:

1. NO USB CARD – 3G modem is not connected to the router or the 3G modem isn’t compatible with the router.
2. Init – Router is busy detecting the 3G modem.
3. Switching – Router is busy verifying the settings.
4. Dialing – 3G modem is trying to establish a connection with the ISP (Internet Service Provider).

3G MOBILE SETUP

Choose Add, Remove or Edit to configure a WAN service For 3G Mobile interface.

Note: If user manually connect up the 3G connection by clicking the 'Manual Dial' button, it will always stay connected, even when DSL connection is back alive.

WIDE AREA NETWORK (WAN) SERVICE FOR 3G MOBILE SETUP

modem status: NO USB CARD

| Interface | Description | Type | Edit | Action |
|-----------|-------------|--------|------|-------------|
| ppp3g0 | mobile | mobile | edit | Manual Dial |

Note: If the router doesn’t detect the 3G modem try restarting the router while the 3G modem is connected and let the router boot up with the 3G modem connected.

If you experience any problems with the router please contact D-Link Technical Support:

Email: support@d-link.co.za

Telephone: 0127412000