

Product Highlights

A Versatile Early Warning System

The built-in alarm alerts you whenever smoke is detected in your home, and triggers cameras and push notifications when you're away

Seamless Connected Home Integration

Connect to your mydlink Connected Home Z-Wave gateway using D-Link's unique protocol, ensuring optimal compatibility

Sets Up in Minutes

Use the intuitive mydlink Home app for your smartphone or tablet to get your home automated in a matter of minutes



DCH-Z310

mydlink™ Z-Wave Smoke Alarm

Features

Easy to Install

- Easily configured using the mydlink Home app for your smartphone or tablet
- Wireless functionality keeps your home free of clutter

Smoke Detection

- Built-in alarm notifies you whenever smoke is detected
- Tamper-proof
- Guaranteed 1-year battery life with low battery indication

Z-Wave Plus

- Uses Z-Wave 500 Series chip
- Speeds of up to 100 kbps

Security

- AES 128-bit encryption for Z-Wave
- Uses D-Link's own protocol for secure communication with all your mydlink Home devices

The DCH-Z310 mydlink™ Z-Wave Smoke Alarm is a Connected Home Z-Wave smoke alarm designed to give you an early warning of developing fires. A built-in alarm alerts you and the neighbors whenever smoke is detected, and can be set up to trigger notifications when you're away. Integrating with D-Link's HNAP protocol, the DCH-Z310 connects seamlessly with your D-Link connected home Z-Wave gateway, guaranteeing compatibility and getting your connected home network up and running right away.

Automate Your Home

Using the latest Z-Wave Plus technology, the mydlink™ Z-Wave Smoke Alarm connects to your Z-Wave gateway, and acts as a trigger for your connected home network whenever smoke is detected. If you're at home, the DCH-Z310's alarm will alert you to any potential danger. Otherwise, the mydlink™ Z-Wave Smoke Alarm can help monitor your home by automatically switching on mydlink-enabled cameras, or receive notifications to give you warnings when you're out. Whatever your home needs, mydlink Connected Home has you covered.

Convenient & Intuitive Setup


The mydlink Home app for your smartphone or tablet allows you to get the DCH-Z310 up and running in minutes. D-Link's unique HNAP protocol is specially designed for D-Link products to seamlessly integrate with one another, ensuring maximum compatibility and greatly speeding up the connection process.

Robust Security Features


The DCH-Z310 mydlink™ Z-Wave Smoke Alarm is protected with powerful 128-bit AES encryption, preventing attackers from disrupting the connection between the alarm and your Z-Wave gateway, giving you peace of mind while you're away from home.

DCH-Z310 mydlink™ Z-Wave Smoke Alarm

Front View



Back View



Technical Specifications

General

Sensor	• Photoelectric smoke sensor	
Alarm	• Built-in 85 dB / 3 m local sounder	
Networking Protocol Support	• Z-Wave v6.02 or above	
Z-Wave Wireless	<ul style="list-style-type: none"> • 868.40 MHz (Europe / China / Singapore / South Africa) • 908.40 MHz (United States / Canada / Mexico / Chile) • 916.00 MHz (Israel) 	<ul style="list-style-type: none"> • 919.80 MHz (Hong Kong) • 921.40 MHz (Australia / New Zealand / Brazil) • 922.50 / 923.90 / 926.30 MHz (Taiwan / JP)
Buttons	• Tamper switch	• Pairing / unpairing / reset button
LED	• Status	

Physical

Dimensions	• Diameter: 120 mm (4.72 inches)	• Depth: 53 mm (2.09 inches)
Weight	• 130 grams (4.59 ounces)	
Power	• Included 3 V CR123A battery	
Temperature	• Operating: 0 to 40 °C (32 to 104 °F)	• Storage: -20 to 70 °C (-4 to 158 °F)
Humidity	• Operating: 10% to 85% non-condensing	• Storage: 5% to 95% non-condensing
Certifications	<ul style="list-style-type: none"> • FCC • CE 	<ul style="list-style-type: none"> • Z-Wave Plus • EN14604 for smoke sensitivity & alarm

Order Information

Part Number	Description
DCH-Z310	mydlink™ Z-Wave Smoke Alarm

Updated 2015/03/13