



Smart[™]

DES-1250G

48-Port 10/100Mbps Smart Switch

With 2 Combo Copper Gigabit/SFP

The DES-1250G Smart Switch presents a cost-effective solution for the small and medium business to implement Ethernet packet switching with easy fine-tuning of network performance and security. This switch comes with high port density of 48 10/100BASE-TX Ethernet ports and 2 combo 1000BASE-T/SFP for flexible copper/fiber Gigabit connection. Port trunks are provided for server deployment and network backbone attachment, while functions important for bandwidth-intensive applications such as Priority Queues and VLANs are supported to enable you to implement Quality of Service (QoS) and security without having to go through complex network management usually found in other managed switches.

High Density With 48 10/100Mbps Ports

The switch provides 48 10/100Mbps ports in a low-profile rack-mountable housing. These ports support auto-sensing and auto-negotiation of network speeds and full/half duplex for connection to workstations and print servers, giving each a dedicated bandwidth. All ports support auto MDI/MDIX crossover, allowing you to connect to any node without the need to change your usual straight-through twisted-pair cables.

2 Combo 1000BASE-T/SFP for Flexible Gigabit Connection

2 combo 1000BASE-T/SFP are provided for flexible copper or fiber Gigabit connection. You can select to install optional transceivers in the SFP slots for short, medium or long-distance fiber backbone attachment. Use of the SFP will disable their corresponding built-in 1000BASE-T connections.

Port Trunks for Aggregated Bandwidths

Ports can be combined together to create multi-link load-sharing aggregated bandwidths to a server or a network backbone. To expand the network, you can also make use of the port trunks to eliminate bottlenecks between the cascaded switches. The switch allows you to combine multiple ports into a trunk, and to create multiple trunks per switch.

VLANs for Enhanced Security & Performance

The switch support VLANs to let you improve security and bandwidth utilization by limiting the broadcast domains and confining intra-group traffic within their segments. To segment

up the network, VLAN-supported workstations and servers that are connected to the switch can be grouped into different Virtual LANs (VLANs).

Quality of Service Support

The switch supports Layer 2 802.1p Priority Queue control to prioritize network packets. Classification of users' data priorities can be based on a data packet Priority Queue. This QoS function support allows you to run bandwidth-intensive and delay-sensitive applications and to attach video servers to the switch for videoconference.

Port Mirroring

The switch supports port mirroring to assist network traffic monitoring. The network administrator can use this function as a diagnostic tool or debugging feature, especially when fending off an attack. It enables you to keep close track of switch performance and alter it if necessary.

Network Management/Monitoring

The switch provides easy web-based switch configuration and network management/monitoring from any networked station that does away with the need for consoles and console cables. Network devices are auto-discovered and displayed on a network topology, and you can receive traps of system events and port errors while monitoring the network status and statistics from any workstation.

Key Features

- 48 10/100BASE-TX Ethernet ports for workstations
- 2 combo 1000BASE-T/SFP for flexible copper/fiber Gigabit connection
- Auto MDI/MDIX cross over for all twisted-pair ports
- 802.3x Flow Control for protection against data loss
- Port mirroring for traffic monitoring
- Port trunks for server/network backbone attachments
- 802.1Q VLAN to enhance security/network performance
- 802.1p Priority Queues, port-based QoS
- Easy web-based switch configuration/management and network monitoring
- Standard rack-mount size

DES-1250G

Technical Specifications

10/100Mbps Smart Switch

General

Port Standards & Functions

- IEEE 802.3 10BASE-T Ethernet (twisted-pair copper)
- IEEE 802.3u 100BASE-TX Fast Ethernet (twisted-pair copper)
- IEEE 802.3ab 1000BASE-T Gigabit Ethernet (twisted-pair copper)
- ANSI/IEEE 802.3 NWay auto-negotiation
- IEEE 802.3x Flow Control
- Port mirroring

Number of Ports

- 48 10BASE-T/100BASE-TX ports
- 2 combo 10/100/1000BASE-T/SFP *

* Use of the SFP will disable their corresponding 10/100/1000BASE-T connections.

SFP Support

- IEEE 802.3z 1000BASE-SX multi-mode fiber (DEM-311GT transceiver)
- IEEE 802.3z 1000BASE-SX multi-mode fiber (DEM-312GT2 transceiver)
- IEEE 802.3z 1000BASE-LX single-mode fiber (DEM-310GT transceiver)
- IEEE 802.3z 1000BASE-LH single-mode fiber (DEM-314GT transceiver)
- IEEE 802.3z 1000BASE-ZX single-mode fiber (DEM-315GT transceiver)
- IEEE 802.3ab 1000BASE-T Cat. 5 twisted-pair (DGS-712 transceiver)

Protocol

CSMA/CD

Data Transfer Rates

- Ethernet:
 - 10Mbps (half duplex)
 - 20Mbps (full duplex)
- Fast Ethernet:
 - 100Mbps (half duplex)
 - 200Mbps (full duplex)
- Gigabit Ethernet:
 - 2000Mbps (full duplex)

Topology

Star

Network Cables

- UTP Cat. 5, Cat. 5e (100 m max.)
- EIA/TIA-568 100-ohm STP (100 m max.)

Full/half Duplex

- Full/half duplex for 10/100Mbps speeds
- Full duplex for Gigabit speed

Media Interface Exchange

Auto MDI/MDIX adjustment for all twisted-pair ports

LED Indicators

- Per device: Power/CPU
- Per 10/100BASE-TX port: Link/Act, 10/100Mbps Speed
- Per 10/100/1000BASE-T port: Link/Act, 100/1000Mbps Speed
- Per SFP: Link/Act

Software

VLAN

- 802.1Q VLAN Tagging
- Maximum 64 VLANs per device

Quality of Service (QoS)

- 802.1p Priority Queues
- Maximum number of queues: 2

Port Trunks

- Up to 6 10/100Mbps port trunks per device (2, 4 or 8 10/100BASE-TX ports per trunk)
- 1 Gigabit port trunk per device (2 1000BASE-T ports per trunk)

Management & Configuration

- Web-based configuration
- Auto-discovery utility
- Configuration reset through software or hardware (reset button)

Performance

Switch Capacity

13.6Gbps

Transmission Method

Store-and-forward

MAC Address Table

4K entries per device

MAC Address Learning

Automatic update

Packet Filtering/Forwarding Rates (half duplex)

Maximum 1,488,095 pps per port

RAM Buffer

1.536MBytes per device

Physical & Environmental

AC Input

100 to 240 VAC 50/60Hz internal universal power supply

Power Consumption

28 watts (max.)

Ventilation

40 x 40 mm DC fan x 1

Operating Temperature

0° to 40 °C

Storage Temperature

-10° to 70 °C

Operating Humidity

10% to 90% non-condensing

Storage Humidity

5% to 90% non-condensing

Dimensions

441 (W) x 309 (D) x 44 (H) mm
19-inch standard rack mounting size

Weight

4.4 kg

Emission (EMI)

- FCC Class A
- CE Class A
- C-Tick

Safety

UL

MTBF

193,317 hrs



ACN 052 202 838

Optional SFP Transceiver

- DEM-310GT** 1000BASE-LX SFP transceiver, single-mode fiber, max. distance 10km, 3.3V
- DEM-311GT** 1000BASE-SX SFP transceiver, multi-mode fiber, max. distance 550m, 3.3V
- DEM-312GT2** 1000BASE-SX SFP transceiver, multi-mode fiber, max. distance 2km, 3.3V

- DEM-314GT** 1000BASE-LHX SFP transceiver, single-mode fiber, max. distance 50km, 3.3V
- DEM-315GT** 1000BASE-ZX SFP transceiver, single-mode fiber, max. distance 80km, 3.3V
- DGS-712** 1000BASE-T SFP transceiver, Cat. 5 twisted-pair, Max. distance 100m, 3.3V

D-Link Worldwide Offices

U.S.A	TEL: 1-800-326-1688	FAX: 1-866-743-4905	Bulgaria	TEL: 359 2 958 22 42	FAX: 359 2 958 65 57
Canada	TEL: 1-905-8295033	FAX: 1-905-8295223	Romania	TEL: 40(0)21 320 23 05	FAX: 40(0)21 320 23 07
Europe (U. K.)	TEL: 44-(0)20-8955-9000	FAX: 44-(0)20-8955-9001	Singapore	TEL: 65-6774-6233	FAX: 65-6774-63225
Germany	TEL: 49-(0)6196-77990	FAX: 49-(0)6196-7799300	Australia	TEL: 61-2-8899-1800	FAX: 61-2-8899-1868
France	TEL: 33 (0)1 30 23 86 88	FAX: 33 (0)1 30 23 86 89	India	TEL: 91-22-2652 6696	FAX: 91-22-2652 8914
Netherlands	TEL: 31-(0)10-282-1445	FAX: 31-(0)10-282-1331	Middle East (Dubai)	TEL: 971-4-391-6480	FAX: 971-4-390-8881
Belgium & Luxemburg	TEL: 32(0)2 517 7111	FAX: 32(0)2 517 6500	Egypt	TEL: 202-291-9035	FAX: 202-291-9051
Switzerland	TEL: 41 (0)1 832 11 00	FAX: 41 (0)1 832 11 01	Turkey	TEL: 90-212-289-5659	FAX: 90-212-289-7606
Austria	TEL: 43 (0)1 240 27 270	FAX: 43 (0)1 240 27 271	Iran	TEL: 90-212-289-5659	FAX: 90-212-289-7606
Sweden	TEL: 46-(0)8 564 619 00	FAX: 46-(0)8 564 619 01	Pakistan	TEL: 92-21-454-8158	FAX: 92-21-453-5103
Denmark	TEL: 45-43-969040	FAX: 45-43-424347	Israel	TEL: 972-9-9715700	FAX: 972-9-9715601
Norway	TEL: 47 99 300 100	FAX: 47 22 30 90 85	Latin America	TEL: 56-2-5838-950	FAX: 56-2-5838953
Finland	TEL: 358-10 309 8840	FAX: 358-10 309 8841	Brazil	TEL: 55-11-2185-9300	FAX: 55-11-2185-9322
Italy	TEL: 39-02-2900-0676	FAX: 39-02-2900-1723	South Africa	TEL: 27-12-665-2165	FAX: 27-12-665-2186
Spain	TEL: 34 93 409 0770	FAX: 34 93 491 0795	Russia	TEL: 7-495-744-0099	FAX: 7-495-744-0099
Portugal	TEL: 351 21 8688493	FAX: 351 21 8622492	Japan	TEL: 81-3-5781-0963	FAX: 81-3-5781-0965
Greece	TEL: 30 210 9914 512	FAX: 30 210 9916902	Korea	TEL: 82-2-890-5491	FAX: 82-2-890-549
Czech Republic	TEL: 420 224 247 500	FAX: 420 224 234 967	China	TEL: 86-10-58635800	FAX: 86-10-58635799
Hungary	TEL: 36 (0)1 461 30 00	FAX: 36 (0)1 461 30 04	Taiwan	TEL: 886-2-6600-0123	FAX: 886-2-6600-3939
Poland	TEL: 48 (0)22 583 92 75	FAX: 48 (0)22 583 92 76	Headquarters	TEL: 886-2-6600-0123	FAX: 886-2-6600-9898