

DSL-2650U 3G setup

1. Enable 3G Backup Service
2. Tick Enable Failover and Fallback
3. Probe Criterion 5 time
4. Probe Cycle every 5 seconds
5. Ping Gateway
6. Select your Specific 3G card
7. Only 8 cards are supported
 - a. BandLuxe C100
 - b. DLink DWM152
 - c. Huawei E160G
 - d. Huawei E220
 - e. Huawei E270
 - f. Huawei E272
 - g. ZTE MF626
 - h. ZTE MF636
8. Dial Number *99#
9. APN is Internet

D-Link

Device Info
Advanced Setup
WAN
3G Configuration
LAN
NAT
Security
Quality of Service
Routing
DNS
DSL
Print Server
Port Mapping
PPTP
Samba Config
Wireless
Diagnostics
Management

Enable 3G Backup Service

3G Backup Service Setting

Select Main Interface: pppoe_0_8_35_1/ppp_0_8_35_1

Select Backup Mechanism: Failover
 Failover and Fallback

Probe Criterion: Probing failed after 5 consecutive times

Probe Cycle: Every 5 seconds

Probe Rule: ping gateway
 ping DNS
 ping host

3G Connection Setting

Select 3G Device: Huawei E220

User Name:

Password:

Dial Number: *99#

APN: internet

Save/Apply