



## DSL-2750U Firmware Upgrade Setup Guide.

You can download the latest firmware for the above mentioned router from the link below:


[ftp://ftp.d-link.co.za/DSL/DSL-2750u%20\(Retail\)/Firmware/Retail%20Version/Hardware%20Version%20T3/](ftp://ftp.d-link.co.za/DSL/DSL-2750u%20(Retail)/Firmware/Retail%20Version/Hardware%20Version%20T3/)

**Note: If you use the wrong firmware you might brick your router and void the warranty.**

Connect with cable to the DSL-2750U.

Once you are connected open your web browser (Internet Explorer, Google Chrome and Firefox).

Type 10.0.0.2 and press Enter.



Username: admin

Password: admin

After entering the username and password click "Login".

You will be directed to the main menu. See below screenshot.

The screenshot displays the D-Link DSL-2750U web interface. At the top, the product page is identified as DSL2750U, with a site map and firmware version AF\_2.00\_R03. The D-Link logo is prominently displayed. The main navigation menu includes SETUP, ADVANCED, MAINTENANCE, STATUS, and HELP. The 'SETUP' menu is expanded, showing options like Wizard, ADSL Interface, Layer2 Interface, WAN Internet Setup, 3G Internet Setup, Wireless Connection, Local Network, IPv6 Local Network, Time and Date, Print Server, and Logout. The 'INTERNET CONNECTION WIZARD' page is active, providing instructions on setting up the Internet connection. It includes a 'Setup Wizard' button and a note about following the Quick Installation Guide. A 'Helpful Hints...' section on the right offers additional guidance for first-time users and advanced users.

Product Page: DSL2750U [Site Map](#) Firmware Version: AF\_2.00\_R03

**D-Link**

DSL-2750U //

SETUP ADVANCED MAINTENANCE STATUS HELP

Wizard  
ADSL Interface  
Layer2 Interface  
WAN Internet Setup  
3G Internet Setup  
Wireless Connection  
Local Network  
IPv6 Local Network  
Time and Date  
Print Server  
Logout

**SETTING UP YOUR INTERNET**

There are two ways to set up your Internet connection. You can use the Web-based Internet Connection Setup Wizard or you can manually configure the connection.

Please make sure you have your ISP's connection settings first if you choose manual setup.

**INTERNET CONNECTION WIZARD**

You can use this wizard for assistance and quick connection of your new D-Link Router to the Internet. You will be presented with step-by-step instructions in order to get your Internet connection up and running. Click the button below to begin.

**Note:** Before launching the wizard, please ensure you have correctly followed the steps outlined in the Quick Installation Guide included with the router.

**Helpful Hints...**

First time users are recommended to run the **Setup Wizard**. Click the **Setup Wizard** button and you will be guided step by step through the process of setting up your ADSL connection.

If you consider yourself an advanced user or have configured a router before, Firstly, click **Setup->Layer2 Interface** to input all the Layer2 settings manually.

Then, click **Setup->WAN Service** to input all the Layer3 settings manually.

[More...](#)

**WIRELESS**

Copyright © 2013-2015 D-Link Systems, Inc.

In the top right hand corner you will see "Firmware Version".

Firmware Version: AF\_2.00\_R03

Go to "Maintenance" then on the left side you'll see "Firmware Update", click on it.

The screenshot shows the router's web interface. At the top, there are navigation tabs: SETUP, ADVANCED, MAINTENANCE (selected), and STATUS. On the left, a sidebar menu includes System, Firmware Update (selected), Access Controls, Diagnostics, System Log, and Logout. The main content area is titled "FIRMWARE UPDATE" and contains the following instructions:

- Step 1:** Obtain an updated firmware image file from your ISP.
- Step 2:** Enter the path to the image file location in the box below or click the "Browse" button to locate the image file.
- Step 3:** Click the "Update Firmware" button once to upload the new image file.

A note states: "NOTE: The update process takes about 2 minutes to complete, and your DSL Router will reboot. Please DO NOT power off your router before the update is complete."

Below the instructions, there is a section titled "FIRMWARE UPDATE" with the following information:

- Current Firmware Version :** AF\_2.00\_R03
- Current Firmware Date :** Apr 29 2015
- Firmware File Name :** [Text input field] [Browse... button]

At the bottom of the section is a large "Update Firmware" button.

Now browse to the new firmware file you have downloaded and click "Update".

The firmware upgrade should take about 2 minutes, the router will restart during the firmware upgrade process.

Once the firmware upgrade is done, log into the router and just verify what the firmware version is on.

If you experience any problems with the router please contact D-Link Technical Support:

Email: support@d-link.co.za

Telephone: 0127412000