



### Setup Guide.

Type in the IP address 10.0.0.2 into your web-browser



You will be prompted with username & password

Username: admin (default)

Password: admin (lower-case)

Login

A screenshot of the D-Link DSL-G225 Web Management login page. The page has a dark grey header with "Product Page: DSL-G225" on the left and "Firmware Version: AF\_3.03\_R05" on the right. Below the header is an orange banner with the D-Link logo. The main content area is white and contains a login form. The form has an orange header with the word "LOGIN". Below this, it says "Welcome to DSL-G225 Web Management". There are two input fields: "Username" with a dropdown menu showing "admin" and "Password" with a text box containing five dots. Below the password field is a checkbox labeled "Remember my login info." and a "Login" button.

Click on “Wireless Connection” then click on Manual Wireless Connection Setup”

DSL-G225	SETUP	ADVANCED	MAINTENANCE	STATUS
Wizard	<b>WIRELESS CONNECTION</b> There are two ways to setup your wireless connection. You can use the Wireless Connection Setup Wizard or you can manually configure the connection. <b>Please note that changes made on this section will also need to be duplicated to your wireless clients and PC.</b>			
xDSL Interface	<b>WIRELESS CONNECTION SETUP WIZARD</b> If you would like to utilize our easy to use Web-based Wizard to assist you in connecting your new D-Link Systems Wireless Router to the Internet, click on the button below. <a href="#">Wireless Connection Setup Wizard</a> <b>Note:</b> Before launching the wizard, please ensure you have followed all steps outlined in the Quick Installation Guide included in the package.			
Layer2 Interface	<b>ADD WIRELESS DEVICE WITH WPS (WI-FI PROTECTED SETUP) WIZARD</b> This wizard is designed to assist you in connecting your wireless device to your router. It will guide you through step-by-step instructions on how to get your wireless device connected. Click the button below to begin. <a href="#">Add Wireless Device with WPS</a>			
WAN Internet Setup	<b>MANUAL WIRELESS CONNECTION OPTIONS</b> If you would like to configure the Internet settings of your new D-Link Router manually, then click on the button below. <a href="#">Manual Wireless Connection Setup</a>			
3G Internet Setup				
Wireless Connection				
Local Network				
IPv6 Local Network				
Time and Date				
Print Server				
Logout				

Once you’ve clicked on “Manual wireless Connection Setup”

Click on “Wireless Basics” seen below

WIRELESS SETTINGS -- WIRELESS BASICS
Configure your wireless basic settings. <a href="#">Wireless Basics</a>

Change the SSID: ( To what the WIFI name you'd like it to be)

Change Country: South Africa

Click: Apply

**WIRELESS NETWORK SETTINGS**

☒ **Enable Wireless**

☐ **Hide Access Point**

☐ **Clients Isolation**

☐ **Disable WMM Advertise**

☒ **Enable Wireless Multicast Forwarding (WMF)**

**SSID:**

**BSSID:**

**Country:**

**802.11 modes:**

**Max Clients:**

Click on "Wireless Connection" then on "Manual Wireless Connection Setup" and then on "Security Settings"

**ADVANCED WIRELESS -- SECURITY SETTINGS**

Allows you to configure security features of the wireless LAN interface.

Make sure that the network authentication is “Mixed WPA2/WPA –PSK”

WPA/WAPI Passphrase: (Own Personal Password)

WPA Group Rekey Interval: 3600

Apply/Save

**MANUAL SETUP AP**

You can set the network authentication method, selecting data encryption, specify whether a network key is required to authenticate to this wireless network and specify the encryption strength.  
Click "Apply/Save" when done.

<b>Select SSID:</b>	Steve G-225 ▾
<b>Network Authentication:</b>	Mixed WPA2/WPA -PSK ▾
Protected Management Frames:	Disabled ▾
<b>WPA/WAPI passphrase:</b>	●●●●●●●●
<b>WPA Group Rekey Interval:</b>	0
<b>WPA/WAPI Encryption:</b>	TKIP+AES ▾
<b>WEP Encryption:</b>	Disabled ▾

[Click here to display](#)

If you experience any problems with the router please contact D-Link Technical Support:

Email: [support@d-link.co.za](mailto:support@d-link.co.za)

Telephone: 0127412000