

Product Highlights

True Gigabit Speed

Enjoy lightning-fast Gigabit speeds without the need for installing a new network card simply by using any available USB Type-C port on your device

Ultra-Fast USB 3.0

SuperSpeed USB 3.0 technology allows you to transfer files up to 10 times faster than with USB 2.0, at up to 5Gbps.

Convenient Compact Design

Its small size allows you to slip it easily into your laptop bag or lay unobtrusively on your desk.



DUB-D410 USB-C to 3-Port USB Hub and Ethernet Adapter

Features

Gigabit Ethernet Connectivity

- Achieve transfer speeds of up to 1 Gbps
- Status LEDs for connection status and data transfer speed
- Auto 10/100/1000 Mbps speed detection with auto-negotiation to always use the highest available speed

USB Type-C with Simple Installation

- Three USB 3.0 SuperSpeed 5 Gbps ports
- Backward compatible with USB 2.0 and USB 1.1 devices
- Simply plug it in and you're ready to go
- No additional hardware or software installation required

Dynamic Power Management

- Reduces power consumption during times of light traffic, when idle, or when the Ethernet cable is unplugged
- Supports the built-in power-saving features of the USB Type-C

The DUB-D410 USB-C to 3-Port USB Hub and Ethernet Adapter allows you to instantly add Gigabit connectivity and three additional USB 3.0 ports to your ultraportable laptop computer. Just plug the DUB-D410 into an available USB Type-C port and you're ready to connect to your network with the speed and reliability of a wired gigabit connection as well connect up to 3 more USB devices.

Gigabit Ethernet Connectivity

The DUB-D410 plugs into any available USB Type-C port on your computer to enable you to connect to an Ethernet network at speeds up to 1 Gbps for up to ten times faster transfer speeds compared to previous standards. High-speed Gigabit Ethernet allows you to transfer large files in no time, or make light work of backups to a server or network storage device. Where wireless connectivity is inconsistent or unavailable, this adaptor offers a seamless wired alternative.

Easy to Install and Use

The DUB-D410 connects to your computer's USB Type-C port and is ready to run as soon as it's plugged in. Plug and play¹ design ensures that there is no need to change any configuration settings or install any software on your computer. For extra convenience, the adapter's compact design means you can easily slip the DUB-D410 into your pocket or laptop bag and take it with you.



DUB-D410 USB-C to 3-Port USB Hub and Ethernet Adapter

Hardware Overview



Technical Specifications		
Connectivity		
Device Interfaces	 RJ-45 Ethernet Port (10/100/1000 Mbps) Three USB Type-A (female) ports 	USB Type-C (male) Connector
LEDs	• Speed (amber)	• Link/ACT (green)
Standards	 USB Specification Version 3.0 USB Specification Version 2.0 USB Specification Version 1.1 OHCI (Open Host Controller Interface) EHCI (Enhanced Host Controller Interface) 	 IEEE 802.3 Ethernet IEEE 802.3u Fast Ethernet IEEE 802.3ab Gigabit Ethernet Supports full duplex and half duplex Wake-On-LAN support
General		
Minimum System Requirements	Microsoft Windows 10/8/7/Vista/XP	Mac OS 10.6 or above
Power Management	Advanced Power Management reduces power usage during idle or light traffic periods	
Physical		
Dimensions (W x H x D)	• 91.96 x 54.93 x 16 mm (3.62 x 2.16 x 0.63 in)	• Cable length: 13 cm (5.12 in)
Weight	• 54.0 g (1.91 oz)	

DUB-D410 USB-C to 3-Port USB Hub and Ethernet Adapter

Power	Input: Bus-powered	• Consumption: 160 mA (Ethernet only), 5 V DC	
Temperature	• Operating: 0 to 40° C (32 to 104 °F)	• Storage: -20 to 70 °C (-4 to 158 °F)	
Humidity	Operating: 10% to 90% RH, non-condensing	Storage: 5% to 90% RH, non-condensing	
Certifications	• CE • IC	• FCC	
Order Information			
Part Number	Description		
DUB-D410	USB-C to 3-Port USB Hub and Ethernet Adapter		

¹ Windows 8/10 and Mac OS 10.11.6 or above operating systems support plug-and-play functionality. Other operating systems may require software installation before the product can be used. Recent versions of Windows require users to confirm before automatic installation can begin.

Updated May 9, 2018

