

[Basic Manual Setup for DWR-957X- How to force 4G only connection]

Step 1: Open your web browser and type **10.0.0.2** into the address bar, then press Enter.



If your device is connected to the router, it will take you to a blue D-Link page asking for a username and password. Default Username is admin, password is admin, unless it was updated.



Step 2: Once logged in, navigate to

Basic Setup → WAN Service



Step 3: Here you will see a table with three options, look for the one that says LTE and then click on edit

WAN ServiceInfo

WAN Name	Interface	Mode	IP Protocol Type	Service Type	Action	
DHCP_WAN_ETH	ETH1	DHCP	IPv4&6	TR069_INTERNET_VOIP	Edit	Delete
PPPoE_WAN_ETH	ETH1	PPPoE	IPv4&6	TR069_INTERNET_VOIP	Edit	Delete
LTE	LTE	DHCP	IPv4	TR069_INTERNET_VOIP	Edit	Delete

Set New WAN

Interface:

Mode:

Step 4: The following screen will appear, click on advance settings.

WAN Service

Connection Name:

Enable: ☒

MTU:

IP Protocol Type:

NAT: ☒

Firewall: ☒

IPv4 Static DNS: ☐

MAC Address Override: ☐

Enable VLAN: ☐

Service Type:

Advanced Settings

Apply Back Refresh

Step 5: Look for where it says NetWork, currently it should be on auto, if you click on auto you will have the option to change it to 4g Only.

Advanced Settings

PIN:

NetWork:

APN:

DialNumber:

Dial UserName:

Dial Password:

DHCP Option 60 Setting: ☐

DHCP Option 66: ☐

DHCP Option 120: ☐

DHCP Option 81 Setting: ☐

Bound Ports: ☐ LAN1 ☐ LAN2 ☐ LAN3 ☐ LAN4
☐ SSID1 ☐ SSID2 ☐ SSID3 ☐ SSID4
☐ SSID5 ☐ SSID6 ☐ SSID7 ☐ SSID8

A grey out port means it has been bound.

Apply Back Refresh

Once you have changed it to 4G only, scroll down and click on apply, the router will now be locked to 4G only.